

ONE GALLON MULTIMIX™
PAINT MIXER

HERO

MAKE INNOVATION

S2460 Countertop



The S2460 vortex one gallon mixer is designed with an Emergency E-Stop button which quietly stops the rotation of the bucket without having to lift the door lid. This unit features HERO's rugged gear driven design, tested to 100,000+ mix cycles

Emergency E-Stop button

Mechanical Timer

All steel construction

Door sensor. Mixer only operates when door is closed

HEAVY DUTY

Ball bearing motor 1/4hp
115v/60hz

QUIET, 3 point heavy duty shock absorbing frame mounts

Unique spill containment system



18" W x 24" D x 25" H
Small footprint for easy fit

HERO ADVANTAGE

- **Emergency E-Stop** button
- Leading Technology at the **best value**
- Rotating door - for "**zero**" vertical clearance
- Improved **stability** and **reduced noise**
- **Vortex mixing** method does not aerate paint
- Easy **drop-in design**

DUAL AXIS™
Vortex technology



Toll Free: +1.800.494.4376

 sales@hero.ca

 www.hero.ca

S2460 TECHNICAL FEATURES

Mixing Motion	Vortex
Load Capacity	Up to 16 lbs.
Container Size(s)	1-gallon Quart, Pint & 1/2 pint (with adapter)
Mix Cycle Time	Up to 6 minutes
Can adapter	Quart, Pint & 1/2 pint (with adapter) included
Bucket clamping	Manual
Machine closing	Metal Door
Timer for mixing cycle	Mechanical timer included
Emergency E-Stop button	Included
Can Holding System	Included
Compliance	CSA C22.2 No. 68 and UL 1450 on 120VAC models
Maximum bucket dimension	North American Standard 1 Gallon Can
Dimension & Weight	W 18" x D 24" x H 25" / 105 lbs.
Power supply	120V 60Hz / 220V 50Hz / 220V 60Hz
Accessories	Floor Stand - stack two mixers or elevate mixer to conveyor height Can/Lid Sealer

TECHNICAL SUPPORT NETWORK THROUGHOUT THE AMERICAS



SERVICE AND SUPPORT

Our customer commitment continues long after the sale with:

- Training
- Multilingual and after hour support
- Factory technicians in US/Canada
- Unmatched, factory-certified Authorized Service Network
- Preventive Maintenance and Extended Warranty programs
- YouTube channel with how-to videos